

Generator de curent monofazat Energy 6500 ME, starter electric



Specificatii tehnice:

Greutate (kg)	91
Putere generator (kVA)	6,0
Curent alternator 230V/400V (A)	26,1/-
Model motor	Subaru, EX40
Combustibil	Benzina-4 timpi
Putere motor (CP)	14
Capacitate cilindrica (cm³)	404
Capacitate rezervor (l)	7,0
Consum la 75% (l/h)	2,2
Dimensiuni LxIxH (mm)	900 x 550 x 600
Dotari standard	priza 230 V, starter manual, starter electric, acumulator 12 V, senzor lipsa ulei, filtru combustibil, protectie termica

AVANTAJE:

- Protectie totala impotriva scurtcircuitelor prin sigurante automate;
- Cadru metalic de protectie, foarte rezistent, vopsit in camp electrostatic.

APLICATII:

- Produce curent electric monofazat necesar in constructii, industrie, comert, agricultura;
- Reprezinta alternativa optima in lipsa conectarii la o retea de electrificare.